## Software installation

**First:** Find the PL2303 driver software, double-click to open the installation. If you have installed configuration software for other related products of our company, you can skip this step. Note: If the current account of the computer is not an administrator, be sure to right-click, select "Run as an administrator".



**Second:** After the driver is installed, the USB to Mini connection is inserted into the computer USB interface. The pop-up box in the lower right corner of the computer indicates that the installation is successful. You can check the COM password number.



You can also view the current COM number at the computer-property-device manager-port.



**Third:** Download the host configuration software and installation. Successful installation appears as shown in the following figure.



Fourth: Operation

4.1 Turn off the host and insert the data line. Then open the software and select the port to which your data line is connected. Click Open Port.

Serial Link		
Prolific USB-to-Serial Comm Port (COM3)	-	Close

4.2 Turn on the host, and you will see some configuration information printed out as shown in the figure in the lower part of the software. Then the startup will be successful.

15:13:24 Device boot detected, version 1.244, try link 15:13:25 Link success! 15:13:25 Channel10 15:13:26 Communication password353224819 15:13:27 Scenario Level1. 15:13:28 Background suppress is enable. 15:13:29 Background Suppress Level3. 15:13:29 Obtain configuration successfully!	*
	-

4.3 After the boot is successful, you can configure it in the middle, and it will still be typed out in the information bar.

gular Configuration   Import Configuration   Serial Link	
Prolific USB-to-Serial Comm Port (COM3)	Close     Refresh
Options	
Channel 75	Communication Password 439026917
Scenario Level           Scenario Level           1Suitable for most places, speak loudly	Background Suppress Level 0Disable background suppress function
TalyType Brand: Datavideo	Model: HS 1200
ReturnVolume Disable Return function	Acoustic echo cancellation
RF Power Level 3	
Ē	Set
10:46:13 Communication password439026917 10:46:14 Scenario Level1.	
10:46:14 Background suppress is disable. 10:46:15 Background Suppress Level1. 10:46:16 Tally Type2. 10:46:17 Gpio Type0. 10:46:18 Return volume0%. 10:46:18 Return volume0%.	

4.4 If the configuration options are not available, you can configure the file import directly. Click the import configuration button above to import the file.

Import Configuration File		
Configuration File : G:\Work\Configuration.txt		
С	lpen	Import

4.5 Click the Open button, select the specified file, and then click Import. Information on whether the configuration was successful will be printed.

Device boot detected, version 1.244, try link... Link success Configuration success----write set 4 10 Configuration success----write set 4 10