Tally interface to vMix

vMix version higher than 20!

1. Install setting tool "TallyInterfaceCfg-Setup.exe" to one computer, connect the computer to Tally interface with network cable as below



Run the setting tool, after successful connection you will see parameter as below:

| 😤 NAYA Tally Interface 设置工具 | |
|------------------------------------------------------|---|
| 心在常语 | |
| K H B/C | 1 |
| | |
| 设备信息 | |
| ((a)) | |
| Γ Å | |
| 2.5.要甘2.5 | |
| 改直叠响 | |
| TINA | |
| 至mal用起 硬件序列号: 180028001347373034353333 版本号: 1.002 | |
| | |
| 网络醌置 | |
| IP地址: 192,168,10,200 网络撞码: 255,255,255,0 | |
| 网关地址: 192_168_10_1 管理PC地址: 192_168_10_100 | |
| | |
| | |
| 和被視式: 1~12路Tally信号 ▼ Tally視式: BMD Tally ▼ | |
| | |
| 进入设置 下 就配置 | |
| | |
| | |
| | |

Please check IP to make sure its at same gateway with vMix. And then please restart the Tally interface. 2. Connect BS350 to vMix with Tally interface as below:



3. Install the plug-in"vMixTally-Setup.exe" to computer with vMix And then run vMix Tally

| 🛃 vMix Tally Naya | |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--|
| 信息栏: | |
| 17:12:43 : Wait Tcp Connetct 17:12:44 : Tcp Link Success 17:12:45 : Tally Interface IP Address:192.168.10.200,Port:54321. 17:12:46 : Tally 1 Red.Tally 2 Green. | |
| | |
| | |
| | |
| | |
| | |
| | |

Turn on the network controller