VC-A61P Firmware(FW) Upgrade Instruction

1 Device and Tool Preparation

1.1 Please prepare following devices and tools before FW upgrade.



2 Connections

- 2.1 Connecting via switch or router
 - 2.1.1 Please ensure the [Ethernet]> [DHCP] in the menu is ON.





3 FW Download

3.1 Open browser and enter the IP address of the camera in the address bar. You can check the IP address from [Status]> [Ethernet] in the menu.



3.2 Enter the account and password to log in webpage.Account: adminPassword: 9999



3.3 Select [Maintenance]> [Choose files...] to select firmware file and press [Submit].





3.4 FW download starts. (Around 2 minutes taken)

	Maintenance	
	FW Upgrade Error Log System Service	
Live View		
Add / Edit Users		
Settings	温擇檔案 VC_A61P_VBBK020 bin submit	
Configuration		
Video		
Camera	8	
Picture	86	
Audio		
Date / Time	8	
Network		
🔍 Maintenance	(1) (1) (1) (1) (1) (1) (1) (1) (1) (1)	
(i) About		
	93 I I I I I I I I I I I I I I I I I I I	
	25	
	<u>8</u>	

3.5 FW upgrade is successful and the camera will reboot.

	Maintenance		
	FW Upgrade Error Lo	g System Service	
Live View	Firmware upgrade is	successful! (Please reboot your system.)	
Add / Edit Users	10		
Settings			
Configuration			
Video			
Camera			
Picture			
Date / Time			
Network			
🔍 Maintenance			
(i) About			



3.6 Please do the [Factory Reset] to ensure the procedure is completed. [Maintenance]> [System Service]> [Reset]

10/1011	Maintenance
	FW Upgrade Error Log System Service
Live View	Factory Reset
Add / Edit Users	
Settings	Factory Reset Reset
Configuration	
Video	Setting Profile
Camera	
Picture	Load Save
Audio	
Date / Time	Baud Rate
Network	

3.7 Click [Yes] and the unit will reboot.

VC-A01P	Maintenance	
	FW Upgrade Error Log Message	- X
Live View	Eastern Reset	
Add / Edit Users	Do you want to do the Pactory Reset?	
Settings	Factory Reset Res Yes No	
Video		
Camera	Profile S - Conformance Test	
Picture	Mode Aux Mode 💌 Apply	
Audio		
Date / Time		
Network		

3.8 Login webpage again and check the FW version from [About]> [Firmware Version]

		Camera ID	M830P-IP
Live View			1/0000 1/0004 1/00042 1/00042 1/00042 1/00 000
Add / Edi	t Users	Firmware Version	Vikuuz_Visuu1_Vibu1z_Vivu1/a_ViPu11_VI1_uzz
Settings		Serial Number	123456789
Configurati	ion		
Video			
Camera			
Picture			
Audio			
Date / Time	e		
Network			

